



TVFC-OT Adiabatic Cooler Once Through Mode

SOFTWARE INSTRUCTIONS






Table of contents

SOFTWARE INSTRUCTIONS


1	Scope	3
	Once Through execution	3
2	Control Logic	4
3	Programmable logic controller	6
	Progammable Logic Controller (PLC)	6
	Display and operations	6
4	Software	8
	Menu overview	8
	Main Loop Menu (P)	9
	User Menu (E)	10
	Working Time Menu (T)	15
	Inputs Outputs Menu (I)	16
	Clock Menu (K)	17
	Logger Menu (H)	17
	System Information (S)	18
	Maintenance Menu (M)	18
5	Alarms and Warnings overview	20
	Alarms overview	20
6	BMS Communication	22
	Available communication protocols and communication cards	22
	Communication table for Modbus RS485	23
	Commissioning guide Modbus RS485	26
7	Further Assistance & Information	28
	More information	28
	The service expert for BAC equipment	28



This manual applies to units configured in Once-Through mode operating on BAC software version V2.0.15 or later, in stand-alone mode.

Once Through execution


The TVFC is a V-shaped dry cooler equipped with adiabatic pre-coolers (1) that cool the warm process fluid (2) by sensible heat transfer. Water flows (3) evenly over evaporative cooling pads located in front of the dry finned coil (4). At the same time axial (5) fans draw air (6) through the pads where a portion of the water evaporates and cools down the saturated air. This increases the cooling capacity of the incoming air for cooling the process fluid (7) inside the coil.





The controller controls the fan speed based on the actual fluid outlet temperature and the standard or freecooling set point, ensuring a minimum electrical consumption and noise level.

The controller will activate and deactivate the adiabatic pre-coolers, one by one, based on a logical combination of fan speed and two ambient temperature switch points.



tamb: ambient temperature

SWP1, SWP2: ambient temperature switchpoints

CWV: adiabatic pre-cooler city water valve

DV: adiabatic pre-cooler drain valve

The standard set point, the free-cooling set point and the two ambient temperature set points are adjustable via the User menu. The controller continuously measures the fluid outlet temperature via a temperature sensor installed in the fluid out pipe and the ambient temperature via a temperature sensor that is factory installed on the unit.

The controller is pre-programmed and ready for operation. However, depending on the size of the installation, you may need to adjust the pre-programmed parameters during start-up.



CAUTION

Changing the PLC's parameters may result in an undesired operation of the unit such as a hunting phenomenon, premature activation of pre-cooling (hence increased water consumption) or in late pre-cooling activation resulting in fluid outlet temperatures exceeding the design temperature.



Progammable Logic Controller (PLC)

The PLC with built-in display:



Display and operations

The controller display contains the screen and six operation keys.

The screen allows eight lines of text. The screen title and the screen reference are always on the top line. Use the operation keys to navigate between the different menus and screens.

	Alarm key	Display the alarm menu.
\odot	Menu key	Display the main menu screen.

ち	Back key	Revert to the previous step or menu.	BAC
↓ ↑	Arrow keys	Navigate between the different screens and menus.	
4	Enter key	Select the marked menu or parameter or enable the change of a parameter.	



Menu overview

Menu	Screen reference	Function	
Main loop	Ρ	 Readout: The unit status (ON/OFF) The fluid outlet and ambient temperature The fan speed The pre-cooler status 	
User	E	 Set: Run authorisation / local ON/OFF Standard and free-cooling set-point PI parameters Ambient temperature switch point for Adiabatic pre-cooling Adiabatic pre-cooler delay Adiabatic pre-cooler cleaning cycle Night quiet mode Time delay on alarm messages BMS communication settings The standard password for the User Menu is "1234". 	
Manufacturer	С	This menu is password protected and is not accessible to unauthorized personnel.	
Working time	Т	Readout the operating hours for the fans and adiabatic pre-cooling.	
Inputs/outputs:	I	Readout the input and output status.	
Clock	K	Set the correct time and date.	
Logger	Н	Readout the alarm and warning history.	
System info	S	Readout the software and bios version.	
Maintenance	М	Set the inputs and outputs manually for test purposes. The standard password for the Maintenance menu is "9876".	

Main Loop Menu (P)





The screens in the Main Loop Menu are read-only and cannot be edited.

Screen P01

5151H 515 BACH1607697	
Seteoint	00.0°C
Tout	00.0 °C
Tamb	00.0 °C
Fan speed	000.0 %
	06.61

Main screen with general information:

- The current time and date.
- The unit serial number and pLAN address: "Ad: 0".
- "Setpoint": the active setpoint for the fluid outlet temperature.
- "Tout": the measured fluid outlet temperature.
- "Tamb": the measured ambient temperature.
- "Fan speed": the current fan speed.
- The unit status: "ON" or "OFF".

Note

Unit status ON implies that the unit is ready to automatically respond to any heat rejection requirement, even in case the fans are temporarily deactivated due to the absence of a heat load.

Screen P03

Tout Tout	208.0°C
Tamb Control	000.0 °C si9nal000.0 %
Local Er BUS En/D	Dis OFF

Overview of all inputs:

- "Tout": the measured fluid outlet temperature.
- "Tamb": the measured ambient temperature.
- "Control signal": the calculated fan speed reference.
- "Local En/Dis": the status of the remote start/stop (dry contact between terminals Y4:1-Y4:4).
- "BUS En/Dis": the status of the BMS controlled variable "Run authorization" (refer to screen E02).

Screen P04

Pre-cooling	문화전
Pre-cooler A	OFF
Pre-cooler B	OFF

Adiabatic pre-cooling status:

- "Pre-cooler A": shows the status of the adiabatic pre-cooler on side A.
- "Pre-cooler B": shows the status of the adiabatic pre-cooler on side B.

Screen P10-P51



rem#fo EBM fan N°2 B10 Offline Addr:002 Current speed 0000rpm Max speed 00000 rpm Power 00000W Current 00000 mA

EC fan information screens:

- The fan status: "Online" or "Offline" and fan address: "Addr: 002".
- "Current speed": the actual fan speed.
- "Max speed": the maximum allowable fan speed.
- "Power": the actual power of the EC fan.
- "Current": Indication of the internal current measured by the EC fan. In most cases this value is a DC current
 which is typically around 1.42 times bigger as the actual current, but for specific type of EC fans the AC
 current could be displayed. For exact evaluation of the fan current please measure the current on the
 terminal strip using an Amperage meter.

Note

In case an EC fan shows the status "Offline", check the power supply to the fan and the Modbus communication wiring to the fan.

User Menu (E)

The screens in the User Menu are editable. The standard password is "1234".


P

Screen E01



- "Language": set the controller language to English, French, Dutch, Spanish or German.
- "Site name": enter the unit serial number or the site name.

Screen E02



- "Run authorization": activate or deactivate the unit. This variable can either be set directly in this screen or via a BMS variable (see section 6: BMS communication).
- "Standard setpoint": the default setpoint for the fluid outlet temperature.
- "Free cooling setpoint": the setpoint for the fluid outlet temperature when the unit operates in free cooling mode. Switch over to free cooling mode via a BMS controlled variable or via the dry contact between terminals Y4:2-Y4:4.

Example

10

The controller controls the fan speed based on the actual fluid outlet temperature and the standard setpoint when the dry contact between terminals Y4:2-Y4:4 is open. When the dry contact between terminals Y4:2-Y4:4 is closed, the controller controls the fan speed based on the actual fluid outlet temperature and the free cooling setpoint.


Screen E03





PI-parameters: these parameters determine the unit's reaction speed to changes in fluid outlet temperature.

- "Prop. Band": set the value for the proportional band of the PI controller.
- "Integr. Time": set the value for the integration time of the PI controller.



band and the integration time, or make the unit react slower by increasing the proportional band and integration time.

Screen E04



Cleaning cycle for the adiabatic pre-coolers:

- "PAD cleaning": allows you to enable or disable the cleaning cycle function. •
- "Interval": set the period (the number of days the adiabatic pre-cooling has not functioned) after which the cleaning cycle must activate.
- "Duration": set the duration for the pre-cooler cleaning cycle.
- Set the time interval for the start of the cleaning cycle.

Example

The pre-cooler cleaning cycle activates the pre-coolers during 120 minutes when the unit has not operated adiabatically for a period of 7 days. The cleaning cycle starts between 14h00 and 18h00.

Note

The controller automatically disables the cleaning cycle when the ambient temperature is below 4°C.

Screens E05-E06



Adiabatic pre-cooler temperature and fan speed switchpoints and time delays:

- "AD switchpnt.1" and "AD switchpnt.2": the temperature switchpoints for the activation of the adiabatic pre-coolers.
- "AD ON fan speed" and "AD OFF fan speed": the fan speed switchpoints for the activation and • deactivation of the adiabatic pre-coolers.
- "AD ON delay" and "AD OFF delay": the time delays for the activation and deactivation of the adiabatic pre-• coolers.



- **Example** The first pre-cooler will activate when the ambient temperature > 25.0°C**AND** the fan speed > 99%, after a 300 seconds delay.
 - The second pre-cooler will activate when the ambient temperature > 28.0°C AND the fan speed > 99% after a 300 seconds delay.
 - The first pre-cooler will deactivate when the ambient temperature < 27.9°C
 - **OR** the fan speed < 70% after a 30 seconds delay.
 - The second pre-cooler will deactivate when the ambient temperature > 24.9°C OR the fan speed < 70% after a 30 seconds delay.

Note


The temperature and fan speed switchpoints determine the operating strategy of the unit. High temperature switchpoints combined with high fan speed switchpoints typically result in high water savings on the adiabatic pre-cooling, while lower temperature and fan speed switchpoints typically result in higher electrical energy savings on the EC fans.

Screens E10-E11-E12

Night Quiet mode E10	DAYTIME	E11	Night Quiet m	ode E12
Night Quiet Mode	MON from00H00	to00H00	AD switchpoint:	
OFF	TUE from00H00		in night quiet	mode
	WED from00H00			
Daytime s.limit 100.0%	THU from00H00		Switchent.1	15.0°C
Night s.limit 080.0%	FRI from00H00		Switchent.2	18.0°C
	SAT from00H00 SUN from00H00			
Control: Clock	SUN from00H00	to00H00		

Night quiet mode: predefine fan speed limits for both day and night time.

- Enable/Disable the Night quiet mode and choose the maximum allowed fan speed during day and night on screen E10:
 - "Night quiet mode": "ON" or "OFF": enable or disable the Night quiet mode.
 - "Daytime speed limit" and "Night time speed limit": set the maximum allowed fan speed during day and night time.
 - "Control": choose the activation mode: either via a BMS controlled variable ("via BMS") or via a predefined time daytime schedule in screen E11("Clock").
 - **"Daytime clock**"Set up a time schedule for the daytime speed limit in screen E11: Monday to Sunday, start time to end time.



- "Via BMS": Use parameter "Night quiet mode day/night time speed limit via BMS" to switch between daytime speed limit and night time speed limit (Refer to the communication tables in Chapter 6).
- Set specific adiabatic pre-cooler switchpoints for Night quiet mode operation in screen E12:
 - **"AD switchpnt.1**" and **"AD switchpnt.2**": specific temperature switchpoints for the activation of the adiabatic pre-coolers when the night time speed limit is active.



Example The Night quiet mode is enabled, with a daytime speed limit of 80% and a night time speed limit of 50%.

During daytime:

- The first pre-cooler will activate when the ambient temperature > 25.0°C **AND** the fan speed > 79.2% (= 99% x 80%) after a 300 second delay.

- The second pre-cooler will activate when the ambient temperature > 28.0°C **AND** the fan speed > 79.2% after a 300 second delay.

- The first pre-cooler will deactivate when the ambient temperature < 27.9°C **OR** the fan speed < 56% (= 70% x 80%) after a 30 second delay.

- The second pre-cooler will deactivate when the ambient temperature > 24.9°C **OR** the fan speed < 56% after a 30 second delay.

During night time:

- The first pre-cooler will activate when the ambient temperature > 15.0°C **AND** the fan speed > 49.5% (= 99% x 50%) after a 300 second delay.

- The second pre-cooler will activate when the ambient temperature > $18,0^{\circ}$ C **AND** the fan speed > 49.5% (= $70\% \times 80\%$) after a 300 second delay.

- The first pre-cooler will deactivate when the ambient temperature < 17.9 °C **OR** the fan speed < 35% (= 70% x 50%) after a 30 second delay.

- The second pre-cooler will deactivate when the ambient temperature < 14.9°C **OR** the fan speed < 35% after a 30 second delay.

Screen E14



Adiabatic pre-cooling deactivation function:

- "Pre-cooler deact.": enable or disable the pre-cooler deactivation function.
- Set the period and the time frame during which the unit deactivates the adiabatic pre-cooling.

Example

When the pre-cooling deactivation function is active, the adiabatic pre-cooling cannot activate between 13:00 and 15:00 o'clock from 15/07 to 15/09.

Screen E15

Forced AD op. Forced AD op. (Authorisation:	mode OFF
Setp. hyst. AD act. delay Ma/SI unit del.	001min

The forced adiabatic operation function allows the unit to activate both pre-coolers simultaneously when the ambient temperature exceeds the fluid outlet setpoint.

- "Forced AD op. mode authorization": enable or disable the forced adiabatic operation function.
- "Setp. hyst.": hysteresis on the fluid outlet temperature setpoint.
- "AD act. Delay": time delay for the activation of the forced adiabatic operation mode.
- "Ma/SI unit delay": time delay for the activation and deactivation of the pre-cooling in forced adiabatic operation mode.

BAC

Forced AD op. E16 Forced AD op. Min fan speed 040 % Max fan speed 090 %

- "Min fan speed": fan speed switchpoint for deactivation of the pre-cooling in the forced adiabatic operation mode.
- **"Max fan speed**": fan speed switchpoint for activation of the pre-cooling in the forced adiabatic operation mode.

Example

Screen E16

The forced adiabatic mode activates when Tamb > ("setpoint" + "setp. hyst.") > $(30^{\circ}C + 0^{\circ}C) > 30^{\circ}C$ during 1 minute.

While in forced adiabatic mode, the pre-cooling activates and deactivates as follows: - When the fans operate between 90% ("**Max fan speed**") and 99%, the pre-cooling activates after 60 s ("**Ma/SI unit delay**").

- When the fans operate at full speed (100%), the pre-cooling activates after 5 s.
- When the fans operate between 30% and 40% ("**Min fan speed**"), the pre-cooling deactivates after 60 s ("**Ma/SI unit delay**").
- When the fans stop running, the pre-cooling deactivates immediately.

Screen E17



Choose the communication protocol: Modbus RS485, Modbus IP, Carel RS485, LON, BacNet IP or BacNet MSTP. Set the communication speed and network address, when applicable. See section 6: BMS communication.

Screen E18



Alarm detection delays:

- "Alarm delay": time delay for EC fan alarms and warnings.
- "Sensor alarm delay": time delay for alarms from the fluid outlet temperature and ambient temperature sensor.
- "Network comm. Loss delay": time delay for the loss of pLAN communication between units (not applicable for stand-alone operation).

```
Note
```

The network communication loss delay is not applicable to stand alone operation.

Screens E19-E20



EC fan emergency mode management:

Enable the EC fan emergency mode to select a fixed fan speed for when the Modbus communication between the controller and the EC fans fails.

In case the EC fan emergency mode is disabled, the fans will continue to operate at the latest known fan speed when the Modbus communication between the controller and the EC fans fails.



- "Emergen. mode": "ON" or "OFF": enable or disable the EC fan emergency mode.
- "Timeout": time delay before the EC fan emergency mode activates.
- **"EM speed 1**": the emergency speed reference in case the ambient temperature ≥ the ambient temperature switchpoint.
- **"EM speed 2**": the emergency speed reference in case the ambient temperature < the ambient temperature switchpoint.
- "Switch Tamb": the ambient temperature switchpoint.

Example When the EC fan emergency mode is enabled, EM speed 1 is set to 100%, EM speed 2 is set to 50% and Switch Tamb is set to 15°C, the EC fans will start running at a fixed speed of 100% in case the Modbus communication between the controller and the EC fans fails when the ambient temperature is 20°C.

In case, the Modbus communication between the controller and the EC fans fails when the ambient temperature is 10°C, the EC fans will start running at a fixed speed of 50%.

Screen E21



Set your own access code for the User Menu.

Working Time Menu (T)

The screens in the Working Time Menu are read only and cannot be edited.

Screen T02

Operating	time T02
Fans	000000H
Step 1 AD Step 2 AD	000000H 000000H

Read the operating time for the EC fans and for both adiabatic pre-coolers, displayed in hours.

Screen T03

T A S
өөн
өөн


Read the operating time for the EC fans, both adiabatic pre-coolers, and the dry and adiabatic operating time displayed in hours.



Inputs Outputs Menu (I)

The screens in the Inputs/Outputs Menu are read only and cannot be edited.

Screens 101-102



Read the analog inputs on the controller:

- "U1: T°C Tout": the current fluid outlet temperature.
- "U2: T°C Tgen": not used.
- "U3: T°C Tamb": the current ambient temperature.

Screen I03



Read the status of the digital inputs on the controller (open/closed):

- "ID4-DI: Inverter AI": VFD status (not used in case of unit working with EC fans).
- "ID5-DI: Free cooling": status of the free cooling mode (dry contact between terminals Y4:2-Y4:4).
- "ID1: On-Off": status of the remote start/stop command (dry contact between terminals Y4:1-Y4:4).
- "U5: Fan Al": not used.


Screen I04

Inputs/Outputs	104
NO8:Alarm(s)	
N07:Warning(s)	
NO3:Pre-Cooler.R	
NO2:Pre-Cooler.L	
N05:	
NO6:Operational	
□lopen - ∎tclosed	

Read the status of the digital outputs on the controller (open/closed).

- "NO8: Alarm(s)": closed contact means that there are one or more alarms active.
- "NO7: Warning(s)": a closed contact means that there are one or more warnings active.
- "NO3: RH Pre-cooler": a closed contact means that the right pre-cooler is active.
- "NO2: LH Pre-cooler": a closed contact means that the left pre-cooler is active.
- "NO5: ---": not used.
- "NO6: Operational": run indication, a closed contact means that the fans are running.

Screen I05




Read the analog outputs on the controller:

- "Y3: N.U": not used.
- "Y4: Fan speed": a 0-10 Volt control signal, which corresponds to the actual fan speed. (0 V = 0%, 10 V = 100%)

Clock Menu (K)



Screen K01



Set the correct time and date. Time format: HH:MM:SS and date format: DD/MM/YY. The software automatically adjusts to Daylight Saving Time.

Logger Menu (H)

The screens in the Logger Menu are read only and cannot be edited.

Screen H01



Read the history of past alarms.

The log shows the alarm message and the time the alarm occurred.






System Information (S)

The screens in System Information are read only and cannot be edited.

Screen S01



"SW Ver.": Current software version installed "OS Ver.": Operating system version "BOOT Ver.": Current boot version

Maintenance Menu (M)


Screen M01

MAINTENANCE	MØ1
Sensor offset Dutlet (U1) 000.0	• C
Corr.:000.0 °C General (U2) 000.0	• C
Corr.:000.0 °C Tamb (U3) 0000.0 Corr.:000.0 °C	°C

Program a sensor offset ("**Corr.**:") to correct the temperature readings for the fluid outlet temperature sensor ("**Outlet (U1)**") and the ambient temperature sensor ("**Tamb (U3)**").

The general outlet temperature sensor is not used in stand-alone operation.

Screen M02



Activate the test mode, which allows to manually set analog and digital outputs and control the EC fans.

• **"Test mode**": activate or deactivate the test mode.

• "Duration": time delay after which the test mode automatically deactivates.

Note

Duration set to 99 min keeps the test mode ON indefinitely
 When the test mode is set to OFF, screens M03 to M07 are invisible.

18

Screen M03

Dig.out over	ride	103
Pre-cooler R	(NØ3):	
	(NØ2):	
Run indicat.	(NØ6):	
Alarm	(108):	
Warning	(NØ7):	
□:Open / ∎ :	Closed	

Manually set the digital outputs:

- "Pre-cooler R": activate or deactivate the right hand pre-cooler.
- "Pre-cooler L": activate or deactivate the left hand pre-cooler.
- "Run indicat.": simulate the run indication.
- "Alarm": simulate an alarm.
- "Warning": simulate a warning.

Screen M05



Manually set the analog outputs:

- "Y3": not used for a unit with EC fan motors.
- "Y4": simulate a 0-10 Volt output.

Screen M06



Manually control the EC fans:

- "Fan speed": 0% to 100%
- "Control type": choose "Global" to operate all fans simultaneously at the same speed or choose "1 by 1" to set the speed for each fan individually via screen M07.

Screen M07

Tes	st indi	v. fat	ns M07
Nº 2	000-0%	Nº 9	000-0%
Nº 3	000-0%	Nº 10	000-0%
Nº 4	888-8%	Nº 11	888-8%
Nº 5	000-0%	Nº 12	000-0%
Nº 6	000-0%	Nº 13	000-0%
Nº 7	000-0%	Nº 14	000-0%
Nº 8	000-0%	Nº 15	000-0%

Set the speed for each fan individually.



19



Alarms overview

- Access the alarms by pressing the alarm button on the controller (triangle with exclamation mark).
- If a particular alarm is no longer present, the alarm message is automatically cleared and the general alarm (NO1) deactivates.
- To see the history of past alarms, check the logger menu.

Note

The Alarm status can be read out via dry contact on terminal Y3: 3/4/5 and the warning status on Y3: 1/2 in the control panel.

Screen AL000

No alarm present.



Screen AL001



Fluid outlet temperature sensor (on input U1) is defective.

- Unit stops working.
- Alarm message AL001 on controller display + general alarm (NO1) activates.





Ambient air temperature sensor (on input U3) is defective.

- Unit remains operational in dry mode, adiabatic operation no longer possible.
- Alarm message AL003 on controller display + general alarm (NO1) activates.

Screens AL010-AL106



Alarms and warnings from the EC fans. Consult BAC factory for more information.

• Unit remains operational, but the defective fan stops working.





Available communication protocols and communication cards

The following communication protocols are available: Carel RS485, Modbus RS485, Modbus TCP/IP, Bacnet IP, Bacnet MS/TP and LON. The table below shows the required communication card and software settings for each communication protocol.



Based on your selection, this manual will only contain the information you require.

Protocol	Communication card reference	Typical parameter settings in the controller	Interface file required?	Available settings
CAREL RS485		Supervision E17 BMS communication CAREL R5485 Baud rate 19200 Address 001	No	- Baudrate: 1200 to 19200 - Slave addresses: 1 to 207
Modbus RS485		Supervision E17 BMS communication Modbus RS485 Baud rate 19200 Address 001 Parity None Stop Bit 2	No	- Baudrate: 1200 to 19200 - Parity: None, Even or Odd - Nbr. stop bits: 1 or 2 - Slave addresses: 1 to 207
Modbus TCP/IP		Supervision E17 BMS communication Modbus IP	No	
Bacnet IP		Supervision E17 BMS communication Bacnet IP	No	

Protocol	Communication card reference	Typical parameter settings in the controller	Interface file required?	Available settings
Bacnet MS/TP		Supervision E17 BMS communication Bacnet MS/TP	No	
LON		Supervision E17 BMS communication Lon	Yes (Xif and Nxe file)	

Communication table for Modbus RS485

			Modbus		
Variable	UOM	R/W	Index	Address	Туре
Fluid outlet temperature	°C	R	1	2	register
Ambient temperature	°C	R	3	4	register
AD switchpoint 1	°C	R/W	4	5	register
AD switchpoint 2	°C	R/W	5	6	register
Night quiet mode: AD switchpoint 1	°C	R/W	8	9	register
Night quiet mode: AD switchpoint 2	°C	R/W	9	10	register
Active setpoint	°C	R	10	11	register
Regular setpoint	°C	R/W	11	12	register
Free cooling setpoint	°C	R/W	12	13	register
Proportional band	°C	R/W	15	16	register
Night quiet mode: daytime speed limit	%	R/W	16	17	register
Night quiet mode: night time speed limit	%	R/W	17	18	register
Daytime clock: Monday start hours	h	R/W	5007	5008	register
Daytime clock: Monday start minutes	m	R/W	5008	5009	register
Daytime clock: Monday end hours	h	R/W	5009	5010	register
Daytime clock: Monday end minutes	m	R/W	5010	5011	register
Daytime clock: Tuesday start hours	h	R/W	5011	5012	register
Daytime clock: Tuesday start minutes	m	R/W	5012	5013	register
Daytime clock: Tuesday end hours	h	R/W	5013	5014	register
Daytime clock: Tuesday end minutes	m	R/W	5014	5015	register
Daytime clock: Wednesday start hours	h	R/W	5015	5016	register
Daytime clock: Wednesday start minutes	m	R/W	5016	5017	register
Daytime clock: Wednesday end hours	h	R/W	5017	5018	register
Daytime clock: Wednesday end minutes	m	R/W	5018	5019	register
Daytime clock: Thursday start hours	h	R/W	5019	5020	register
Daytime clock: Thursday start minutes	m	R/W	5020	5021	register
Daytime clock: Thursday end hours	h	R/W	5021	5022	register
Daytime clock: Thursday end minutes	m	R/W	5022	5023	register
Daytime clock: Friday start hours	h	R/W	5023	5024	register
Daytime clock: Friday start minutes	m	R/W	5024	5025	register
Daytime clock: Friday end hours	h	R/W	5025	5026	register
Daytime clock: Friday end minutes	m	R/W	5026	5027	register
Daytime clock: Saturday start hours	h	R/W	5027	5028	register
Daytime clock: Saturday start minutes	m	R/W	5028	5029	register



				Modbus	
Variable	UOM	R/W	Index	Address	Туре
Daytime clock: Saturday end hours	h	R/W	5029	5030	register
Daytime clock: Saturday end minutes	m	R/W	5030	5031	register
Daytime clock: Sunday start hours	h	R/W	5031	5032	register
Daytime clock: Sunday start minutes	m	R/W	5032	5033	register
Daytime clock: Sunday end hours	h	R/W	5033	5034	register
Daytime clock: Sunday end minutes	m	R/W	5034	5035	register
Night quiet mode: Control type (0: clock - 1: via BMS)		R/W	5035	5036	register
Integration time	sec	R/W	5037	5038	register
Cleaning cycle: interval	days	R/W	5038	5039	register
Cleaning cycle: duration	min	R/W	5039	5040	register
AD ON fan speed	%	R/W	5040	5041	register
AD OFF fan speed	%	R/W	5041	5042	register
AD ON delay	sec	R/W	5042	5043	register
AD OFF delay	sec	R/W	5043	5044	register
Unit pLAN address		R	5051	5052	register
Pre-cooling Deactivation function: start day		R/W	5056	5057	register
Pre-cooling Deactivation function: start month		R/W	5057	5058	register
Pre-cooling Deactivation function: end day		R/W	5058	5059	register
Pre-cooling Deactivation function: end month		R/W	5059	5060	register
Pre-cooling Deactivation function: start hour	h	R/W	5060	5061	register
Pre-cooling Deactivation function: end hour	h	R/W	5062	5063	register
Alarm delay	sec	R/W	5068	5069	register
Sensor alarm delay	sec	R/W	5069	5070	register
Fan speed	%	R	5077	5078	register
EC fan N°2: actual speed	rpm	R	5078	5079	register
EC fan N°2: maximum allowable speed	rpm	R	5079	5080	register
EC fan N°2: actual power	W	R	5080	5081	register
EC fan N°3: actual speed	rpm	R	5082	5083	register
EC fan N°3: maximum allowable speed	rpm	R	5083	5084	register
EC fan N°3: actual power	W	R	5084	5085	register
EC fan N°4: actual speed	rpm	R	5086	5087	register
EC fan N°4: maximum allowable speed	rpm	R	5087	5088	register
EC fan N°4: actual power	W	R	5088	5089	register
EC fan N°5: actual speed	rpm	R	5090	5091	register
EC fan N°5: maximum allowable speed	rpm	R	5091	5092	register
EC fan N°5: actual power	W	R	5092	5093	register
EC fan N°6: actual speed	rpm	R	5094	5095	register
EC fan N°6: maximum allowable speed	rpm	R	5095	5096	register
EC fan N°6: actual power	W	R	5096	5097	register
EC fan N°7: actual speed	rpm	R	5098	5099	register
EC fan N°7: maximum allowable speed	rpm	R	5099	5100	register
EC fan N°7: actual power	W	R	5100	5101	register
EC fan N°8: actual speed	rpm	R	5102	5105	register
EC fan N°8: maximum allowable speed	rpm	R	5103	5103	register
EC fan N°8: actual power	W	R	5104	5104	register
EC fan N°9: actual speed	rpm	R	5106	5107	register
EC fan N°9: maximum allowable speed	rpm	R	5107	5108	register
EC fan N°9: actual power	W	R	5108	5109	register
EC fan N°10: actual speed	rpm	R	5110	5111	register
EC fan N°10: maximum allowable speed	rpm	R	5111	5112	register
EC fan N°10: actual power	W	R	5112	5113	register
EC fan N°11: actual speed	rpm	R	5112	5115	register
EC fan N°11: maximum allowable speed	rpm	R	5115	5116	register

				Modbus	
Variable	UOM	R/W	Index	Address	Туре
EC fan N°11: actual power	W	R	5116	5117	register
EC fan N°12: actual speed	rpm	R	5118	5119	register
EC fan N°12: maximum allowable speed	rpm	R	5119	5120	register
EC fan N°12: actual power	W	R	5120	5121	register
EC fan N°13: actual speed	rpm	R	5122	5123	register
EC fan N°13: maximum allowable speed	rpm	R	5123	5124	register
EC fan N°13: actual power	W	R	5124	5125	register
EC fan N°14: actual speed	rpm	R	5126	5127	register
EC fan N°14: maximum allowable speed	rpm	R	5127	5128	register
EC fan N°14: actual power	W	R	5128	5129	register
EC fan N°15: actual speed	rpm	R	5130	5131	register
EC fan N°15: maximum allowable speed	rpm	R	5131	5132	register
EC fan N°15: actual power	W	R	5132	5133	register
Standard/Free cooling switch over		IX.	0102	0100	register
(0: Standard / 1: Free cooling)		R/W	1	2	coil
Free cooling status (0: OFF / 1: ON)		R	2	3	coil
Night quiet mode (0: disable / 1: enable)		R/W	4	5	coil
Night quiet mode status (0: not active / 1: active)		R	5	6	coil
Night quiet mode: clock mode active		R	6	7	coil
(0: NO / 1: YES) Night quiet mode: BMS mode active			7	0	il
(0: NO / 1: YES)		R	1	8	coil
Night quiet modeday/night time speedlimit via BMS (0:night / 1:day)		R/W	8	9	coil
Run authorization (0: OFF / 1: ON)		R/W	9	10	coil
Cleaning cycle (0: disable / 1: enable)		R/W	10	11	coil
Pre-cooling deactivation function (0: disable / 1: enable)		R/W	11	12	coil
NO1 relay output status: Alarm(s) (0:No alarm / 1:Alarm)		R	13	14	coil
NO2 relay output status: Warning(s) (0:No warning / 1:Warning)		R	14	15	coil
NO3 relay output status: RH Pre-cooler (0:open / 1:closed)		R	15	16	coil
NO4 relay output status: LH Pre-cooler (0:open / 1:closed)		R	15	17	coil
NO6 relay output status: Run indication (0:stopped /		ĸ	10	17	COII
1:running)		R	18	19	coil
B6 Dig In status - Free cooling mode (0: Disabled / 1:Enabled)		R	21	22	coil
ID1 - Remote start/stop status (0: off / 1: on)		R	22	23	coil
Alarm sensor B1 (fluid outlet temperature sensor)		R	24	25	coil
EBM N°2 - alarm/warning present		R	29	30	coil
EBM N°3 - alarm/warning present		R	30	31	coil
EBM N°4 - alarm/warning present		R	31	32	coil
EBM N°5 - alarm/warning present		R	32	33	coil
EBM N°6 - alarm/warning present		R	33	33	coil
EBM N°7 - alarm/warning present		R	33	35	coil
EBM N°8 - alarm/warning present		R	34	35	
					coil
EBM N°9 - alarm/warning present		R	36	37	coil
EBM N°10 - alarm/warning present		R	37	38	coil
EBM N°11 - alarm/warning present		R	38	39	coil
EBM N°12 - alarm/warning present		R	39	40	coil
EBM N°13 - alarm/warning present		R	40	41	coil
EBM N°14 - alarm/warning present		R	41	42	coil
EBM N°15 - alarm/warning present		R	42	43	coil
Alarm present		R	59	60	coil
				-	coil
					coil coil
Alarm present Unit status (0: OFF / 1: ON) Warning present Alarm sensor B4 (ambient temperature sensor)		R R R R	59 63 66 67	64 67 68	





Commissioning guide Modbus RS485

This guide will show the commissioning procedure to activate the Carel PLC with the Modbus RS485 protocol.

Requirements:

- PC/Laptop
- Carel PLC with Carel RS485 serial card (PCOS004850)
- RS485 to USB converter

Next steps will be executed during this guide:

- 1. Hardware setup
- 2. Check the configuration of the Carel PLC

HARDWARE SETUP

Make sure the Carel RS485 serial card (PCOS004850) is installed on the Carel PLC.



Connect the serial card to your laptop by using the RS485 to USB convertor.



Make sure that the polarity of the wiring between the serial card and the convertor is correct. The wiring should be as follows:

Rx+/Tx+ -> +

-> -

Rx-/Tx-

It might be possible that other convertor suppliers use other terminology. In this case they will probably use the next descriptions.

A -> +

B -> -

Do not connect the GND connection when you use the convertor in combination with your laptop. You might get wrong readouts when the GND is connected to your laptop. The GND connection only needs to be used when connecting the serial card with the customer network.


Now power the controller.



CAREL PCO5 CONFIGURATION

Make sure the Carel PLC is configured correctly.

- Go to the User (E) menu
- Enter the password "0000"
- Go to the User screen E17
- Define the protocol as Modbus RS485



The controller uses these factory settings:

Baud rate	19200
Address	001
Parity	None
Stop bit	2
Data bits	8

These settings can be adjusted via the control panel.

The Carel PLC and the serial card are now ready to be integrated in the Modbus RS485 protocol installation.

TVFC-OT

FURTHER ASSISTANCE & INFORMATION

More information

REFERENCE LITERATURE

- Eurovent 9-5 (6) Recommended Code of Practice to keep your Cooling System efficient and safe. Eurovent/Cecomaf, 2002, 30p.
- Guide des Bonnes Pratiques, Legionella et Tours Aéroréfrigérantes. Ministères de l'Emploi et de la Solidarité, Ministère de l'Economie des Finances et de l'Industrie, Ministère de l'Environnement, Juin 2001, 54p.
- Voorkom Legionellose. Minsterie van de Vlaamse Gemeenschap. December 2002, 77p.
- Legionnaires' Disease. The Control of Legionella Bacteria in Water Systems. Health & Safety Commission. 2000, 62p.
- Hygienische Anforderungen an raumlufttechnische Anlagen. VDI 6022.

INTERESTING WEBSITES

Baltimore Aircoil Company	www.BaltimoreAircoil.com
BAC Service website	www.BACservice.eu
Eurovent	www.eurovent-certification.com
European Working Group on Legionella Infections (EWGLI)	EWGLI
ASHRAE	www.ashrae.org
Uniclima	www.uniclima.fr
Association des Ingénieurs et techniciens en Climatique, Ventilation et Froid	www.aicvf.org
Health and Safety Executive	www.hse.gov.uk

ORIGINAL DOCUMENTATION

This manual is originally made in English. Translations are provided for your convenience. In the event of discrepancies, the English original text shall prevail over the translation.

The service expert for BAC equipment

We offer tailored services and solution for BAC cooling towers and equipment.

- · Original spare parts and fill -for an efficient, safe and year round reliable operation.
- Service solutions preventive maintenance, repairs, refurbishments, cleaning and disinfection for reliable trouble-free operation.
- Upgrades and new technologies save up energy and improve maintenance by upgrading your system.
- Water treatment solutions equipment for controlling corrosion scaling and proliferation of bacteria.

For more details, contact your local BAC representative for further information and specific assistance at www.BACservice.eu





BAC

L	





BAC

L	





BAC

L	

COOLING TOWERS

CLOSED CIRCUIT COOLING TOWERS

ICE THERMAL STORAGE

EVAPORATIVE CONDENSERS

HYBRID PRODUCTS

PARTS, EQUIPMENTS & SERVICES

BLUE by nature GREEN at heart



www.BaltimoreAircoil.com Europe@BaltimoreAircoil.com

Please refer to our website for local contact details.

Industriepark - Zone A, B-2220 Heist-op-den-Berg, Belgium

© Baltimore Aircoil International nv